






































# The Hong Kong University of Science and Technology

## Cisco Unified IP Phone 6945 User Quick Reference



Service Features	Access
<b>Internal Call</b>	Dial 4 digits extension no.
<b>External Call</b>	Dial 9 + tel. no.
<b>Speakerphone</b> (Handsfree Speaker)	
• On	Press  ( Green Light is on )
• Off	Press  again
<b>Audio Mute</b>	
• On	During a call, press  ( Red Light is on )
• Off	Press  again
<b>Redial</b> (redial last dialed number)	Press { <b>Redial</b> }
<b>Call Hold</b>	
• put a line on hold	Press  (the 1 <sup>st</sup> line button flashes green)
• reconnect the call	Press { <b>Resume</b> } or 
<b>Call Transfer</b>	
• transfer	 + Ext. No. / 9 + Tel. No. +  / { <b>Transfer</b> }
• reconnect (if the line is no answer / busy)	Press { <b>Cancel</b> } + { <b>Resume</b> }
<b>Conference</b> ( 8 Parties Audio/Video Calls )	
• set up	 + Ext. No. / 9 + Tel. No. +  / { <b>Conference</b> }
• reconnect (if the line is no answer / busy)	Press { <b>Cancel</b> } + { <b>Resume</b> }
• remove a party from conference	Press Show Details +  + select a party + { <b>Remove</b> }
<b>Call Pickup</b>	
• group pickup	Lift the handset and press { <b>PickUp</b> }
<b>Call Park</b> (Hold a call and retrieve it at another phone)	
• park a call	During a call, press { <b>Park</b> } (Screen shows a 4-digit Park No.)
• reconnect a parked call	Enter the Park No. at another phone
<b>Call Forward</b>	
• set up (all calls)	Press { <b>Forward All</b> } + Ext. No. (Screen shows  & "Forwarded to XXXX")
• cancel	Press { <b>Forward Off</b> }

Service Features		Access
<b>Immediate Divert</b> ( <i>send an incoming call to voicemail system</i> )		<b>Press { Divert }</b>
<b>Access Voicemail System</b> (Note: The new voicemail system number is <b>5000</b> instead of 8000) <ul style="list-style-type: none"> <li>internal access</li> </ul>		When having voicemail, Message Waiting Indicator is on (Red).  Press  or dial <b>5000</b> , enter pin no.#
<ul style="list-style-type: none"> <li>external access</li> </ul>		Dial <b>2358 5000</b> , enter 4-digit extension no. & pin no.#
<b>Call Log</b> ( <i>total stores up to 150 records</i> ) <ul style="list-style-type: none"> <li>dial from call log</li> </ul>		 <b>Settings / Applications</b> + <b>(1. Call History)</b> + select a call log record + Press { <b>All Call</b> } or { <b>Missed Call</b> } <b>Received</b> -  , <b>Placed</b> -  , <b>Missed</b> -  + { <b>Edit Dial</b> } to edit the displayed number if necessary + { <b>Dial</b> } / lift the handset to start calling
<b>Personal Directory (Personal Address Book)</b> <ul style="list-style-type: none"> <li>sign in for Personal Address Book (PAB)</li> </ul>		 + <b>(1. Personal Directory)</b> + enter User ID & Phone PIN + { <b>Submit</b> } Use the Navigation bar and button to scroll and select
<ul style="list-style-type: none"> <li>search for an entry</li> </ul>		Log into PAB + enter Search Criteria + { <b>Find</b> }
<ul style="list-style-type: none"> <li>dial from entry</li> </ul>		Search for an entry + { <b>Dial</b> } + select a Phone No. + { <b>OK</b> } + { <b>OK</b> }
<b>Arrow Keys</b> 	Up	Press up arrow key to review call history. Select a number to edit and dial
	Down	Press down arrow key to review the speed dial buttons, highlight the stored speed dial, then lift up handset to dial
<b>Phone Settings Web Portal (Cisco Unified CM End User Options)</b> (On-campus access only)		Launch a web browser, & go to <a href="https://cm.uc.ust.hk/ccmuser">https://cm.uc.ust.hk/ccmuser</a> Login using Portal Password
<b>Contrast</b>		Press  + <b>(2. Preferences)</b> + <b>(2. Contrast)</b> +  to adjust + { <b>Save</b> } to confirm
<b>Ring Tone</b>		Press  + <b>(2. Preferences)</b> + <b>(1. Ring Tone)</b> +  to change + select Ring Tone + { <b>Play</b> } to listen / { <b>Set</b> } + { <b>Apply</b> } to use
<b>Volume</b>		
<ul style="list-style-type: none"> <li>adjust the handset, headset and speaker volume</li> </ul>		When handset, headset or speaker is in use (off hook), press: 
<ul style="list-style-type: none"> <li>adjust the ringer volume</li> </ul>		When handset, headset and speaker is not in use (on hook), press: 

Buttons / Keys											
											
Handsfree Speaker	Audio Mute	Hold	Transfer	Conference	Navigation (Up, Select, Down)	Voicemail	Settings / Application	Contacts	Volume Control	Forwarded icon	{ } Softkey